

# EXPLORER™ 700

## QUICK GUIDE

### Start up

1. Connect the cable(s).
2. Press and hold the power button next to the display until the green power indicator lights up.
3. Enter the SIM PIN if required.
4. Adjust the antenna position to obtain the maximum signal strength, and accept.

NOTE: If you need to repoint the antenna later, enter the display menu system and select **SETTINGS > POINT NOW**.

When the display shows READY, you can make a call or run a data session.

### Voice call

If you are using a Bluetooth handset, the handset must be paired and placed close to the EXPLORER™ 700.

To make a call from the EXPLORER™ 700, dial **00 <country code> <phone number>** followed by # or off-hook key.

Example: Thrane & Thrane A/S in Denmark:  
**00 45 39558800 #**


NOTE: There are two audio qualities for voice: Standard voice and 3.1 kHz audio.

To force the call to use Standard voice, dial **1 \*** before the number.

To force the call to use 3.1 kHz Audio, dial **2 \*** before the number.

To make a call to the EXPLORER™ 700, dial **+870 <mobile number>**

NOTE: There are two mobile numbers for voice, one for 3.1 kHz Audio and one for Standard voice.



### Fax call

To send a fax from the EXPLORER™ 700, dial **00 <country code> <phone number> #**

Example: Thrane & Thrane A/S in Denmark:  
**00 45 39558888 #**

NOTE: For an analog fax, the audio quality must be set to 3.1 kHz Audio. For an ISDN fax, the audio quality must be set to UDI.

To force 3.1 kHz Audio, dial **2 \*** before the number.

To force UDI, dial **3 \*** before the number.

To send a fax to the EXPLORER™ 700, dial **+870 <mobile number>**

### Local call

To make a local call from a Bluetooth phone to a standard phone, dial **0301** or **0302** followed by off-hook key.

To make a local call from a standard phone to a Bluetooth phone, dial the number of the Bluetooth phone followed by #.

To make a local call to an ISDN phone, dial **the number of the ISDN phone** followed by # or off-hook key.

For information on allocation of local numbers, refer to the User manual.

## Start/Stop Streaming on LAN

1. Enter the menu system and select **CONNECT**.
2. Select the Streaming Profile you want to activate on the LAN or WLAN interface.
3. Select **START** or **STOP**.

NOTE: When running a Streaming session you are charged for the time you are connected. A started Streaming session will stay active until you stop it.

The Streaming Profiles must first be defined and activated in the LAN window of the web interface. Refer to the User manual.

## Accessing the web interface

1. Connect a PC to the EXPLORER™ 700.
2. Start your Internet browser.
3. Enter the IP address of the web interface.  
The default IP address is 192.168.0.1.

The IP address is found in the menu system, by selecting **PROPERTIES > TERMINAL > IP ADDRESS**.

## Send SMS

1. In the web interface, select **MESSAGES > Write Message**
2. Type the message.
3. Type in the phone number as follows:  
**00 <country code> <phone number>**.
4. Select **Delivery Notification On or Off**.
5. Click **Send**.

## Shortcuts in the menu system

To turn pointing sound on/off press ▲ or ▼ .

To activate stealth mode, press **C + OK**.

To exit the menu system, press and hold **C** for one second.

## DISPLAY MENUS

